WIDE BAND O2 SYSTEMS

Name:	**Wide Band Oxygen Sensor**	
Part #:	**Edelbrock #91170 & 91177**	
Range:	10.0-20.0	
Units:	A/F	
Type:	y = ax + b	
Calibration:	**Bits**	**Value**
	0	10.00
	4095	20.00

Wide Band Oxygen Sensor		
Edelbrock #91170 & 91177		
.65-1.40		
Ratio		
y = ax + b		
Bits	**Value**	
0	0.68	
4095	1.36	

Wide Band Oxygen Sensor		
AFX		
9.0-16.0		
A/F		
y = ax + b		
Bits	**Value**	
0	9.00	
4095	16.00	

Wide Band Oxygen Sensor		
AFX		
.60-1.10		
Ratio		
y = ax + b		
Bits	**Value**	
0	0.61	
4095	1.09	

Name:	**Wide Band Oxygen Sensor**	
Part #:	**Twin Tech**	
Range:	10.0-20.0	
Units:	A/F	
Type:	y = ax + b	
Calibration:	**Bits**	**Value**
	0	10.00
	4095	20.00

Wide Band Oxygen Sensor		
Twin Tech		
.65-1.40		
Ratio		
y = ax + b		
Bits	**Value**	
0	0.68	
4095	1.36	

Wide Band Oxygen Sensor		
AEM		
10.0-20.0		
A/F		
y = ax + b		
Bits	**Value**	
0	10.00	
4095	19.98	

Wide Band Oxygen Sensor		
AEM		
.65-1.40		
Ratio		
y = ax + b		
Bits	**Value**	
0	0.68	
4095	1.36	

Name:	**Wide Band Oxygen Sensor**	
Part #:	**Inovate**	
Range:	7.35-22.39	
Units:	A/F	
Type:	y = ax + b	
Calibration:	**Bits**	**Value**
	0	7.35
	4095	22.39

Wide Band Oxygen Sensor		
Inovate		
.50-1.54		
Ratio		
y = ax + b		
Bits	**Value**	
0	0.50	
4095	1.54	

Wide Band Oxygen Sensor		
Fast		
9.6-21.1		
A/F		
y = ax + b		
Bits	**Value**	
0	9.60	
3354	21.10	

Wide Band Oxygen Sensor		
Fast		
.65-1.43		
Ratio		
y = ax + b		
Bits	**Value**	
0	0.65	
3354	1.43	

Name:	**Wide Band Oxygen Sensor**	
Part #:	**EFI Technology**	
Range:	8.82-27.56	
Units:	A/F	
Type:	y = ax + b	
Calibration:	**Bits**	**Value**
	1122	8.82
	1278	9.19
	1442	9.70
	1597	10.29
	1761	10.95
	1917	11.69
	2080	12.42
	2236	13.30
	2392	14.55
	2564	15.95
	2720	19.11
	2884	22.79
	3039	27.56

Wide Band Oxygen Sensor		
EFI Technology		
.60-1.88		
Ratio		
y = ax + b		
Bits	**Value**	
1122	0.60	
1278	0.63	
1442	0.66	
1597	0.70	
1761	0.75	
1917	0.80	
2080	0.85	
2236	0.91	
2392	0.99	
2564	1.09	
2720	1.30	
2884	1.55	
3039	1.88	

Wide Band Oxygen Sensor		
Dyno Jet		
10.0-18.0		
A/F		
y = ax + b		
Bits	**Value**	
0	10.00	
4095	18.00	

Wide Band Oxygen Sensor		
Dyno Jet		
.65-1.25		
Ratio		
y = ax + b		
Bits	**Value**	
0	0.68	
4095	1.22	